

The Quint Audio P9 is a high end 8-IN/8-OUT digital loudspeaker management system that provides all the processing and control necessary to drive A-series amplifiers for Quint Audio loudspeaker systems. It has 4 analog inputs, 2 AES inputs, 8 analog outputs and 64x64 Dante card option.



FEATURES:

- Optional user-installed MOD-Dante-ETH module 64x64 I/O of Dante network audio bi-directionally over a standard RJ45 (Ethernet) cable.
- Build-In temperature regulated ventilator
- IP-reset button
- TCP-IP connection for system setup, monitoring and control via fully manageable remote PC software

SYSTEM PARAMETERS:

DSP engine	40-bit floating point DSP 48 / 96kHz selectable sampling rate
Propagation delay	4ms@48kHz 2ms@96kHz

CONNECTORS:

analog / AES input	6x XLR symmetrical
analog outputs	8x XLR symmetrical
ethernet	RJ45
recovery	USB
power	PowerCon

GENERAL:

mains	100-240V
AC mains frequency range	50-60Hz
dimensions (wxhxd)	19" x 44.45mm x 229mm / 1U
weight	3.5 kg